IN THE CLAIMS

Please amend the claims as follows:

1. (Currently Amended) A method of providing a digital signal processing function f to an executing device having at least one processor in an obfuscated form; the function f including a function cascade including a plurality of signal processing functions f_i, $1 \leq i \leq N$, for processing a digital signal input x to yield a digital signal ~~output~~ output, ~~such as, $FC_1(x)=f_N \circ \cdots \circ f_1(x)$~~, the method including:

performing the following steps by at least one processor of the executing device:

selecting a set of $2N$ invertible permutations p_i, $1 \leq i \leq 2N$;

calculating a set of N functions g_i, where g_i is functionally equivalent to

$p_{2i}^{-1} \circ f_i \circ p_{2i-1}$, for $1 \leq i \leq N$;

calculating a set of N-1 functions h_i, where h_i is functionally equivalent to

$p_{2i-1}^{-1} \circ p_{2i-2}$, for $2 \leq i \leq N$;

equipping the executing device with an execution device function cascade that includes $y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1$, where $y_1,..., y_N$ are function ~~parameters~~ parameters, ~~(such as, $ED_1(y_1,..., y_N) = y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1)$~~,

providing the functions $g_1,..., g_N$ to the executing device; and

in the executing device, applying the execution device function cascade to the functions $g_1,..., g_N$ ~~(such as $ED_1(g_1,..., g_N))$~~, wherein the execution of the g_i and h_i functions by the executing device in an interleaved manner enables the functionality of the execution device function cascade to be achieved without function f being directly recognizable.

2. (Currently Amended) A method of providing a digital signal processing function f as claimed in claim 1, wherein the execution device function cascade includes

$y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1 \circ p_1^{-1}$ ~~(such as $ED_2(y_1,..., y_N) = y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1 \circ p_1^{-1})$~~.

3. (Currently Amended) A method of providing a digital signal processing function f as claimed in claim 1, wherein the function cascade starts with a further signal processing function f_0 ~~(such as $FC_2(x) = f_N \circ ... \circ f_1 \circ f_0(x)$)~~ and the execution device function cascade includes

$y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1 \circ S_1$ ~~(such as $ED_3(y_1,...,y_N) = y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1 \circ S_1)$~~,

where S_1 is functionally equivalent to $p_1^{-1} \circ f_0$.

4. (Currently Amended) A method of providing a digital signal processing function f as claimed in claim 1, wherein the execution device function cascade includes

$p_{2N} \circ y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1$ ~~(such as $ED_4(y_1,...,y_N) = p_{2N} \circ y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1)$~~.

5. (Currently Amended) A method of providing a digital signal processing function f as claimed in claim 1, wherein the function cascade ends with a further signal processing function f_{N+1}, ~~(such as $FC_3(x) = f_{N+1} \circ f_N \circ ... \circ f_1(x)$)~~ and the execution device function cascade includes

$S_2 \circ y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1$ ~~(such as, $ED_5(y_1,...,y_N) = S_2 \circ y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1)$~~

where S_2 is functionally equivalent to $f_{N+1} \circ p_{2N}$.

6. (Original) A method of providing a digital signal processing function f as claimed in claim 1, including obtaining a unique identity of the executing device and/or user of the executing device; the set and/or sequence of $2N$ invertible permutations p_i being unique for the obtained identity.

7. (Original) A method as claimed in claim 1, wherein the step of equipping the executing device with the execution device function cascade includes providing the execution device function cascade embedded in a software program for execution by a processor in the executing device.

8. (Original) A method as claimed in claim 7, wherein the step of providing the functions $g_1,...,$ g_N to the executing device includes providing the functions $g_1,..., g_N$ in the form of a plug-in for the program.

9. (Original) A method as claimed in claim 7, wherein the step of providing the functions $g_1,...,$ g_N to the executing device includes embedding the functions $g_1,..., g_N$ in the software program by applying the execution device function cascade to the function parameters $g_1,..., g_N$.

10. (Currently Amended) A computer program product <u>stored on a non-transitory computer</u> <u>readable storage medium that is</u> operative to cause a processor in an execution device to execute a digital signal processing function f including a function cascade including a plurality of signal processing functions f_i, where $1 \le i \le N$, for processing a digital signal input x to yield a digital signal output ~~(such as, $FC_1(x) = f_N \circ ... \circ f_1(x)$)~~, by:

    performing the following steps by at least one processor of the execution device:

        loading an execution device function cascade that includes

$y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1$, where $y_1,..., y_N$ are function parameters,

        loading a set of functions $g_1,..., g_N$;

        applying the execution device function cascade to the set of functions $g_1,..., g_N$;

    where:

        g_i is functionally equivalent to $p_{2i}^{-1} \circ f_i \circ p_{2i-1}$, for $1 \le i \le N$;

        h_i is functionally equivalent to $p_{2i-1}^{-1} \circ p_{2i-2}$, for $2 \le i \le N$; and

        p_i is an invertible permutation, for $1 \le i \le 2N$.

11. (Currently Amended) A system for providing a digital signal processing function f to an executing device in an obfuscated form; the system including a server (610) and an executing device (620); the function f including a function cascade including a plurality of signal processing functions f_i, $1 \le i \le N$, for processing a digital signal input x to yield a digital signal output<u>;</u> ~~(such as, $FC_1(x) = f_N \circ ... \circ f_1(x)$)~~;

    the server including a processor (612) for performing the following steps, under control of a program:

        selecting a set of $2N$ invertible permutations p_i, $1 \le i \le 2N$;

        calculating a set of N functions g_i, where g_i is functionally equivalent to

$p_{2i}^{-1} \circ f_i \circ p_{2i-1}$, for $1 \le i \le N$; and

calculating a set of N-1 functions h_i, where h_i is functionally equivalent to $p_{2i-1}^{-1} \circ p_{2i-2}$, for $2 \le i \le N$; and

means (614) for equipping the executing device with an execution device function cascade that includes $y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1$, where $y_1,..., y_N$ are function ~~parameters~~ parameters, ~~(such as $ED_1(y_1,..., y_N) = y_N \circ h_N \circ y_{N-1} \circ h_{N-1} \circ ... \circ y_1)$,~~ and

means (616) for providing the functions $g_1,..., g_N$ to the executing device; and the executing device (620) including:

means (626) for obtaining the functions $g_1,..., g_N$ from the server; and

a processor (622) for, under control of a program, loading the execution device function cascade and applying the loaded execution device function cascade to the functions $g_1,..., g_N$, ~~(such as, $ED_1(g_1,..., g_N)$),~~ wherein the execution of the g_i and h_i functions by the executing device in an interleaved manner enables the functionality of the execution device function cascade to be achieved without function f being directly recognizable.

12. (Currently Amended) An execution device (620) for use in the system as claimed in claim 11; the executing device including:

means (626) for obtaining the functions $g_1,..., g_N$ from the server; and

a processor (622) for, under control of a program, applying the execution device function cascade to the functions $g_1,..., g_N$ ~~(such as, $ED_1(g_1,..., g_N)$)~~ and applying the applied device function cascade to the digital signal input x.

13.   (Currently Amended) A method of providing a digital signal processing function f to a plurality of executing devices, each identified by a unique index j, in an obfuscated, anonymous form; the function f including a function cascade including a plurality of signal processing functions f_i, where $1 \le i \le N$, for processing a digital signal input x to yield a digital signal output ~~(such as, (such as, $FC_1(x) = f_N \circ ... \circ f_1(x))$~~,the method including:

performing the following steps by at least one processor:

selecting a set of $2N$ invertible permutations p_i, where $1 \le i \le 2N$;

calculating a set of N functions g_i, where g_i is functionally equivalent to

$$p_{2i}^{-1} \circ f_i \circ p_{2i-1}, \quad 1 \leq i \leq N;$$

selecting for each device j a corresponding set and/or sequence of $2N$ invertible

permutations $p_{j,i}$, that is unique for the device and/or a user of the device;

calculating for each executing device j a corresponding set of N-1 functions $h_{j,i}$,

where $h_{j,i}$ is functionally equivalent to $p_{j,2i-1}^{-1} \circ p_{j,2i-2}$ for $2 < i < N$;

equipping each executing device j with a respective execution device function

cascade $ED_j(y_1,\ldots,y_N)$ that includes $y_N \circ h_{j,N} \circ y_{N-1} \circ h_{j,N-1} \circ \ldots \circ y_1$;

equipping each executing device j with a respective loader function

$loader_j(x_1,\ldots,x_N) = (l_{j,1} \circ x_1 \circ r_{j,1},\ldots,l_{j,N} \circ x_N \circ r_{j,N})$, where $l_{j,i}$, is functionally equivalent to

$p_{j,2i}^{-1} \circ p_{2i}$ and $r_{j,i}$ is functionally equivalent to $p_{2i-1}^{-1} \circ p_{j,2i-1}$;

providing to the executing device the functions $g_1,\ldots,g_N$; and

in the executing device, executing $ED_j(loader_j(g_1,\ldots,g_N))$.

14.   (Original) A method of providing a digital signal processing function f as claimed in claim 13, including providing $g_1,\ldots,g_N$ to each executing device through broadcasting and/or distribution on a storage medium with a same content for each executing device.

15.   (Original) A method of providing a digital signal processing function f as claimed in claim 14, including also providing the digital signal input x to each executing device through broadcasting and/or distribution on a storage medium with a same content for each executing device.

16.   (Original) A method of providing a digital signal processing function f as claimed in claim 13, including providing to executing device j through a one-to-one communication channel and/or a storage medium with a device-specific content at least one the following sets of corresponding functions: $h_{j,i}$, $l_{j,i}$, or $r_{j,i}$.

17.   (Previously Presented) A method of providing a digital signal processing function f as claimed in claim 1, wherein the function f is a decryption function based on a Feistel cipher network and each of the signal processing functions f_i is a respective Feistel decryption round function.

18. (Currently Amended) A method of providing a digital signal processing function f as claimed in claim 17, wherein each of the permutations p_i is a Feistel transformer where a function Q operating on a sequential pair <x, y> is a Feistel transformer if there exist invertible functions Q_x and Q_y and $Q(\langle x, y \rangle) = \langle Q_x(x), Q_y(y) \rangle$, where $Q_x(x) \oplus Q_x(y) = Q_x(x \oplus y)$ and

$$Q_y(x) \oplus Q_y(y) = Q_y(x \oplus y) \underline{.}$$

19. (Currently Amended) A computer program product <u>stored on a non-transitory computer readable storage medium that is</u> operative to cause a processor in an execution device j to execute a digital signal processing function f including a function cascade including a plurality of signal processing functions f_i, where $1 \le i \le N$, for processing a digital signal input x to yield a digital signal output ~~(such as, $FC_1(x) = f_N \circ ... \circ f_1(x)$)~~, the method including:

    performing the following steps by at least one processor of the execution device:

        loading an execution device function cascade that is unique for the execution device and that includes $y_N \circ h_{j,N} \circ y_{N-1} \circ h_{j,N-1} \circ ... \circ y_1$, where $y_1,..., y_N$ are function parameters,

        loading a loader function

        $loader_j(x_1,...,x_N) \equiv (l_{j,1} \circ x_1 \circ r_{j,1},...,l_{j,N} \circ x_N \circ r_{j,N})$, loading a set of functions

        $g_1,..., g_N$;

        applying the loader function to the set of functions $g_1,..., g_N$ yielding a set of functions $g_{j,1},..., g_{j,N}$ and applying the execution device function cascade to the set of functions $g_{j,1},..., g_{j,N}$, where:

            g_i is functionally equivalent to $p_{2i}^{-1} \circ f_i \circ p_{2i-1}$, for $1 \le i \le N$;

            p_i is an invertible permutation, for $1 \le i \le N$;

$h_{j,i}$ is functionally equivalent to $p_{j,2i-1}^{-1} \circ p_{j,2i-2}$ for $2 \leq i \leq N$;

$l_{j,i}$ is functionally equivalent to $p_{j,2i}^{-1} \circ p_{2i}$;

$r_{j,i}$ is functionally equivalent to $p_{2i-1}^{-1} \circ p_{j,2i-1}$; and

$p_{j,i}$ are invertible permutations, for $1 \leq i \leq 2N$, being unique for the device and/or a user of the device.

20. (Currently Amended) A system for providing a digital signal processing function f to a plurality of executing devices, in an obfuscated, anonymous form; the system including a server and a plurality of executing devices, each identified by a unique index j; the function f including a function cascade including a plurality of signal processing functions f_i, where $1 \leq i \leq N$, for processing a digital signal input x to yield a digital signal output; ~~(such as,~~

~~$FC_1(x) = f_N \circ ... \circ f_1(x))$~~;

the server including a processor for performing the following steps, under control of a program:

selecting a set of $2N$ invertible permutations p_i, where $1 \leq i \leq 2N$;

calculating a set of N functions g_i, where g_i is functionally equivalent to

$p_{2i}^{-1} \circ f_i \circ p_{2i-1}$, for $1 \leq i \leq N$;

selecting for each device j a corresponding set and/or sequence of $2N$ invertible permutations $p_{j,i}$, that is unique for the device and/or a user of the device;

calculating for each executing device j a corresponding set of N-1 functions $h_{j,i}$, where $h_{j,i}$ is functionally equivalent to $p_{j,2i-1}^{-1} \circ p_{j,2i-2}$ for $2 \leq i \leq N$;

equipping each executing device j with a respective execution device function cascade $ED_j(y_1,..., y_N)$ that includes $y_N \circ h_{j,N} \circ y_{N-1} \circ h_{j,N-1} \circ ... \circ y_1$;

equipping each executing device j with a respective loader function

$loader_j(x_1,...,x_N) = (l_{j,1} \circ x_1 \circ r_{j,1},...,l_{j,N} \circ x_N \circ r_{j,N})$, where $l_{j,i}$ is functionally equivalent to

$p_{j,2i}^{-1} \circ p_{2i}$ and $r_{j,i}$ is functionally equivalent to $p_{2i-1}^{-1} \circ p_{j,2i-1}$; and

providing to the executing device the functions $g_1,..., g_N$; and

AMENDMENT AND RESPONSE UNDER 37 C.F.R. § 1.116 - EXPEDITED PROCEDURE   **Page 9**
Serial Number:10/596,336   Dkt: 2069.078US1
Filing Date: June 9, 2006
Title: BLOCK CIPHERING SYSTEM, USING PERMUTATIONS TO HIDE THE CORE CIPHERING FUNCTION OF EACH ENCRYPTION
     ROUND

each executing device j,

means for obtaining the functions g_1,..., g_N from the server; and

a processor for, under control of a program:

loading an execution device function cascade that is unique for the

execution device and that includes $y_N \circ h_{j,N} \circ y_{N-1} \circ h_{j,N-1} \circ ... \circ y_1$, where y_1,..., y_N

are function parameters,

loading a loader function

$$loader_j(x_1,...,x_N) \equiv (l_{j,1} \circ x_1 \circ r_{j,1},...,l_{j,N} \circ x_N \circ r_{j,N})$$

applying the loader function to the set of functions g_1,..., g_N yielding a set

of functions $g_{j,1}$,..., $g_{j,N}$; and

applying the execution device function cascade to the set of functions

$g_{j,1}$,..., $g_{j,N}$.

21. (Original) An execution device for use in the system as claimed in claim 20; where the

executing device is identified by a unique index j; and includes:

means for obtaining the functions g_1,..., g_N from the server; and

a processor for, under control of a program:

loading an execution device function cascade that is unique for the execution

device and that includes $y_N \circ h_{j,N} \circ y_{N-1} \circ h_{j,N-1} \circ ... \circ y_1$, where y_1,..., y_N are function

parameters,

loading a loader function $loader_j(x_1,...,x_N) \equiv (l_{j,1} \circ x_1 \circ r_{j,1},...,l_{j,N} \circ x_N \circ r_{j,N})$

applying the loader function to the set of functions g_1,..., g_N yielding a set of

functions $g_{j,1}$,..., $g_{j,N}$; and

applying the execution device function cascade to the set of functions $g_{j,1}$,..., $g_{j,N}$

where:

g_i is functionally equivalent to $p_{2i}^{-1} \circ f_i \circ p_{2i-1}$ for $1 \leq i \leq N$;

p_i is an invertible permutation, for $1 \leq i \leq N$;

$h_{j,i}$ is functionally equivalent to $p_{j,2i-1}^{-1} \circ p_{j,2i-2}$ for $2 \leq i \leq N$;

$l_{j,i}$ is functionally equivalent to $p_{j,2i}^{-1} \circ p_{2i}$;

$r_{j,i}$ is functionally equivalent to $p_{2i-1}^{-1} \circ p_{j,2i-1}$; and

$p_{j,i}$ are invertible permutations, for $1 \leq i \leq 2N$, being unique for the device and/or a user of the device.